

# Flex Max<sup>®</sup> RF Amplifiers

## FM321e-LE 1 GHz Line Extender Amplifiers

### FEATURES

- Simplify plant upgrades with modular RF design
- Improve amplifier reach with optional GaN technology and increased station tilt
- Maintain current amplifier spacing with high output GaAs technology
- Expand return path bandwidth with plug-in diplex filter support to 85 MHz
- Minimize RF drift over temperature with optional analog or QAM ALC



### PRODUCT OVERVIEW

The Flex Max<sup>®</sup> FM321e-LE 1 GHz line extender amplifier is designed to extend existing systems or build out new networks, providing operators with the ability to quickly add high-output capacity with minimal disruption. The FM321e-LE features a host of drop-in module options that operators can use to cost-effectively upgrade legacy 9-LH series housings for integration into 1 GHz architectures, while FM321e-LE units with 110 or 230 VAC powering options are excellent solutions for deployments in high-rise buildings and medium-to-large MDUs.



The FM321e-LE provides operators with superior forward and return path performance. The unit features 1 GHz GaAs technology that mitigates distortion and minimizes performance issues relative to Composite Second Order (CSO) and Composite Triple Beat (CTB), while optional GaN technology provides higher output capacity for extended reach or fiber deep applications. The unit’s return path circuitry, installed on the PC board, uses a hybrid amplifier with an improved compression point and bit error rate (BER) for digitally loaded traffic. Directional coupler forward output and return input test points isolate their respective input signals from the effects of reflections in the cable. The FM321e-LE’s design also provides slope and gain control flexibility in the forward path, which minimizes amplifier respacing during upgrades. On the return output, an attenuator and an equalizer circuit controlled by a plug-in attenuator allow for accurate return path alignment.

ARRIS also offers a QAM Channel Automatic Level Control (ALC) Pilot Frequency option, which allows operators to choose between 609 MHz or 711 MHz pilot frequencies.

| PLATFORM COMPATIBILITY |              |              |              |              |
|------------------------|--------------|--------------|--------------|--------------|
| Platform               | Philips LE9x | Philips MMLE | Flex Max 320 | Flex Max 321 |
| Upgrade to FM321e      | Yes          | Yes          | Yes          | Yes          |

| HOUSING COMPATIBILITY |      |      |
|-----------------------|------|------|
| Housing               | 7-LH | 9-LH |
| Upgrade to FM321e     | Yes* | Yes  |

\* Requires input and output baseplate upgrade kit part number: 1505595-001

| RELATED PRODUCTS      |                        |
|-----------------------|------------------------|
| FM601e-T/B            | STARLINE RF Amplifiers |
| FM901e-T/B            | FM331                  |
| Installation Services |                        |

## SPECIFICATIONS – GaAs (ALC)

| Specifications <sup>15</sup>                         | Units       | Forward  | Return                           |
|--|-------------|--|----------------------------------|
| Frequency Split                                      | MHz         | 54 – 1002<br>85 – 1002<br>105 – 1002 <sup>14</sup> | 5 – 42<br>5 – 65<br>5 – 85       |
| Flatness   | dB          | ± 0.8  | ± 0.9                            |
| Full Gain (without EQ and ALC)                       | dB          | 41   | 20                               |
| Operation Gain (-0,+1.5 dB) <sup>1,2</sup>           | dB          | 33   | 20                               |
| ALC Control Range                                    | dB          | ± 3  | NA                               |
| Noise Figure (without EQ) <sup>3</sup>               | dB          | 10/9.5/9/10  | 6.5                              |
| Standard Slope Reference Frequency                   | MHz         | 1002/870/550/54                                    | F <sub>MAXRTN</sub> /5           |
| Reference Output Level <sup>5,6</sup>                | dBmV        | 52/49.5/44/35                                      | 37/37                            |
| Operating Tilt                                       | dB          | 17   | NA                               |
| Carrier to Interference Ratio                        |             |  |                                  |
| Channels, Number of NTSC <sup>4</sup>                |             | 79   | 6                                |
| Composite Triple Beat (CTB)                          | -dBc        | 75   | 80                               |
| Cross Modulation (XM)                                | -dB         | 67   | 70                               |
| Composite Second Order (CSO)                         | -dBc        | 73   | 78                               |
| Carrier to Intermodulation Noise (CIN) <sup>8</sup>  | dB          | 63   | —                                |
| Channels, Number of 256 QAM <sup>9</sup>             |             | 154  | —                                |
| Carrier to Intermodulation Noise (CIN) <sup>10</sup> | dB          | 63   | —                                |
| Test Point Accuracy (-20 dB)                         | dB          |  |                                  |
| Input Test Point                                     |             | ± 1.25 (54 – 1002)                                 | ± 0.5 (5 – F <sub>MAXRTN</sub> ) |
| Output Test Point                                    |             | ± 1.25 (54 – 1002)                                 | ± 1.5 (5 – F <sub>MAXRTN</sub> ) |
| Return Loss  | dB          | 16   | 16                               |
| Hum Modulation @ 15A                                 | -dBc        |  |                                  |
| 5 – 10 MHz   |             | —  | 55                               |
| 11 – F <sub>MAXRTN</sub> MHz                         |             | —  | 60                               |
| F <sub>MINFWD</sub> – 1002 MHz                       |             | 60   | —                                |
| DC Voltage   | VDC         |  | 24 ± 0.5                         |
| Current DC Max./Typical                              | mA          |  | 865/800                          |
| Power Consumption Max./Typical                       | W           |  | 27/23                            |
| Input Voltage Range                                  | VAC         |  |                                  |
| 90 VAC HFC   |             |  | 45 – 90                          |
| 110 VAC Mains  |             |  | 90 – 130                         |
| 230 VAC Mains  |             |  | 205 – 253                        |
| HFC AC Current Draw Max./Typical <sup>13</sup>       | A           |  |                                  |
| @ 90 VAC   |             |  | 0.375/0.32                       |
| @ 60 VAC   |             |  | 0.61/0.52                        |
| AC Bypass Current (all ports)                        | A           |  | 15                               |
| Chrominance/Luminance Delay                          | ns/3.58 MHz |  |                                  |
| Channel 2  |             | 28   | —                                |
| Channel 3  |             | 12   | —                                |
| Channel 4  |             | 7  | —                                |
| Channel 5  |             | 4  | —                                |
| Return Group Delay                                   | ns          |  |                                  |
| 5.5 – 7 MHz  |             | —  | 52                               |
| 10 – 11.5 MHz  |             | —  | 13                               |
| 35 – 36.5 MHz  |             | —  | 10                               |
| 38.5 – 40 MHz  |             | —  | 28                               |

## SPECIFICATIONS – GaN (ALC)

| Specifications <sup>15</sup>                         | Units       | Forward  | Return                           |
|--|-------------|--|----------------------------------|
| Frequency Split                                      | MHz         | 54 – 1002<br>85 – 1002<br>105 – 1002 <sup>14</sup> | 5 – 42<br>5 – 65<br>5 – 85       |
| Flatness   | dB          | ± 0.8  | ± 0.9                            |
| Full Gain (without EQ and ALC)                       | dB          | 41   | 20                               |
| Operation Gain (-0,+1.5 dB) <sup>1,2</sup>           | dB          | 33   | 20                               |
| ALC Control Range                                    | dB          | ± 3  | NA                               |
| Noise Figure (without EQ) <sup>3</sup>               | dB          | 10/9.5/9/10  | 6.5                              |
| Standard Slope Reference Frequency                   | MHz         | 1002/870/550/54                                    | F <sub>MAXRTN</sub> /5           |
| Reference Output Level <sup>5,7</sup>                | dBmV        | 56/53.5/48/39                                      | 37/37                            |
| Operating Tilt                                       | dB          | 17   | NA                               |
| Carrier to Interference Ratio                        |             |  |                                  |
| Channels, Number of NTSC <sup>4</sup>                |             | 79   | 6                                |
| Composite Triple Beat (CTB)                          | -dBc        | 70   | 80                               |
| Cross Modulation (XM)                                | -dB         | 65   | 70                               |
| Composite Second Order (CSO)                         | -dBc        | 73   | 78                               |
| Carrier to Intermodulation Noise (CIN) <sup>8</sup>  | dB          | 60   | —                                |
| Channels, Number of 256 QAM <sup>9</sup>             |             | 154  | —                                |
| Carrier to Intermodulation Noise (CIN) <sup>10</sup> | dB          | 59   | —                                |
| Test Point Accuracy (-20 dB)                         | dB          |  |                                  |
| Input Test Point                                     |             | ± 1.25 (54 – 1002)                                 | ± 0.5 (5 – F <sub>MAXRTN</sub> ) |
| Output Test Point                                    |             | ± 1.25 (54 – 1002)                                 | ± 1.5 (5 – F <sub>MAXRTN</sub> ) |
| Return Loss <sup>11</sup>                            | dB          | 16   | 16                               |
| Hum Modulation @ 15A                                 | -dBc        |  |                                  |
| 5 – 10 MHz   |             | —  | 55                               |
| 11 – F <sub>MAXRTN</sub> MHz                         |             | —  | 60                               |
| F <sub>MINFWD</sub> – 1002 MHz                       |             | 60   | —                                |
| DC Voltage   | VDC         |  | 24 ± 0.5                         |
| Current DC Max./Typical                              | mA          |  | 865/800                          |
| Power Consumption Max./Typical                       | W           |  | 27/23                            |
| Input Voltage Range                                  | VAC         |  |                                  |
| 90 VAC HFC   |             |  | 45 – 90                          |
| 110 VAC Mains  |             |  | 90 – 130                         |
| 230 VAC Mains  |             |  | 205 – 253                        |
| HFC AC Current Draw Max./Typical <sup>13</sup>       | A           |  |                                  |
| @ 90 VAC   |             |  | 0.375/0.32                       |
| @ 60 VAC   |             |  | 0.61/0.52                        |
| AC Bypass Current (all ports)                        | A           |  | 15                               |
| Chrominance/Luminance Delay                          | ns/3.58 MHz |  |                                  |
| Channel 2  |             | 28   | —                                |
| Channel 3  |             | 12   | —                                |
| Channel 4  |             | 7  | —                                |
| Channel 5  |             | 4  | —                                |
| Return Group Delay                                   | ns          |  |                                  |
| 5.5 – 7 MHz  |             | —  | 52                               |
| 10 – 11.5 MHz  |             | —  | 13                               |
| 35 – 36.5 MHz  |             | —  | 10                               |
| 38.5 – 40 MHz  |             | —  | 28                               |

## SPECIFICATIONS – MECHANICAL

| Specifications                | Units       | Forward                                       | Return |
|-------------------------------|-------------|---|--------|
| Operating Temperature Range   | C (F)       | -40° to +60° (-40° to +140°)                  |        |
| Housing Dimensions, L x W x D | inches (mm) | 8.9 L x 7.5 W x 5.5 D (226 L x 191 W x 140 D) |        |
| Weight                        | lb (kg)     | 7.4 (3.35)                                    |        |

## NOTES:

- Forward spacing at highest frequency with PEQ-1G-xx equalizer installed.
- Return spacing is with a 0 dB attenuator installed in the return EQ location. Return EQ circuitry is built into main PCB. As the attenuator value increases, the return equalization insertion loss at  $F_{MAXRTN}$  MHz also increases.
- The noise figure specification is "Typical" within specified passband.
- Analog channels occupying the 54 to 550 MHz frequency range with 256-QAM channels to 1002 MHz at -6 dBc below equivalent video channels.
- Recommended maximum return output level includes loss due to equalizer.
- At specified operational tilt, maximum equivalent analog output level for 1 GHz loading is 56.5 dBmV @ HF for GaAs.
- At specified operational tilt, maximum equivalent analog output level for 1 GHz loading is 59 dBmV @ HF for GaN.
- Systems operating with digitally compressed channels or equivalent broadband noise from 550 to 1002 MHz at levels 6 dB below equivalent video channels will experience a composite intermodulation distortion (CIN) appearing as noise in the 54 to 550 MHz frequency spectrum.
- 256-QAM channels occupy 54 to 1002 MHz with 3 channels replaced by analog channels for CCRN measurement.
- Systems operating with digitally compressed channels from 54 to 1002 MHz at levels 6 dB below equivalent video channels will experience a composite intermodulation distortion (CIN) appearing as noise relative to any remaining analog channels.
- Output return loss may derate to 15 dB above 600 MHz.
- Test point tolerance is with input attenuator position terminated into 75  $\Omega$ .
- The power supply is internal to the RF module. Refer to drawing #333995-32.  
For 60 VAC powering: AC power consumption in watts divided by a factor of 43 = Amps required.  
For 90 VAC powering: 67 VAC, 1.03 x (AC power consumption in watts divided by voltage) = Amps required.  
For 67 to 90 VAC, AC power consumption in watts divided by 65 = Amps required.
- For frequency split 85/105 MHz roll-off from 105 MHz to 102 MHz < 1.0 dB. Group delay from 103.25 MHz to 105.25 MHz is < 22 ns
- Full list of specifications available in FM321e Equipment Manual, document number 1505332.

## REQUIRED ACCESSORIES

| Part Number | Description  |
|-------------|--|
| PEQ-1G-00   | One of the following per FM321e Forward 1002 MHz equalizer (0 dB) -or-<br>Forward 1002 MHz equalizer (values 2 to 20 dB in 1 dB steps) -or-<br>Cable simulator (values 2 to 12 dB in 1 dB steps) |
| PEQ-1G-XX   |  |
| PCS-1G-XX   |  |
| 10-Axx.0-WC | Plug-in pad/attenuator (values 0 to 26 dB in 1 dB steps)<br>Also used for Return Equalization  |

## Customer Care

Contact Customer Care for product information and sales:

- United States: 866-36-ARRIS
- International: +1-678-473-5656

**Note:** Specifications are subject to change without notice.

**Copyright Statement:** © 2019 ARRIS Enterprises LLC. All rights reserved. ARRIS and the ARRIS logo are trademarks of ARRIS International plc and/or its affiliates. All other trademarks are the property of their respective owners. No part of this publication may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from ARRIS International plc ("ARRIS"). ARRIS reserves the right to revise this publication and to make changes in content from time to time without obligation on the part of ARRIS to provide notification of such revision or change.

FM321eLE\_DS\_29MAY19

(rev 05-2019)