

Headend Optics Platform (CH3000)

OS32M2B-00-AS

Dual-packaged 2x1 Optical Switches for DWDM Forward and Return Paths

FEATURES

- Dual-packaged non-latching 2x1 optical switches
- Fast switching speed (< 5 ms typical)
- Wide range of user-settable switching thresholds for analog and digital transport applications: -22 to +22 dBm
- Low insertion loss
- Dual wavelength operating windows (1263.5-1357.5 nm and 1423.5-1617.5 nm)
- Switching function designed to detect the loss of the return path DWDM wavelengths on ITU Ch 40 to Ch 59 while supporting forward path DWDM wavelengths on ITU Ch 20 to Ch 39
- Each 2x1 switch allows simultaneous counter-propagating signals
- Low power consumption
- Hot plug-in/out
- Local and remote status monitoring and control
- High packaging density: up to 56 switches per chassis
- Occupies one half-depth slot



PRODUCT OVERVIEW

The ARRIS OS32M2B Dual-packaged 2x1 optical switch module for the CH3000 platform offers fast switching times, low insertion loss, and high packaging density.

These units are available as dual packaged 2x1 switches in a single-width, half-depth module. The switches have been designed with a wide dynamic threshold adjustment range to support a wide combination of both analog and digital transmission applications. The modules are self-sensing of fiber restoration for maximum network reliability and efficiency, and are fully controllable both locally and remotely.

In the OS32M2B, the light from A and B inputs are detected and used to control the switch (i.e., having high isolation from any input signals that may be present at the “Out” ports).

The features of the OS3200 series of optical switches make them ideally suited to applications where high reliability is required and space and power consumption are important considerations.

SPECIFICATIONS

Characteristics	Specification
Physical	
Dimensions	6.5" D x 5.25" H x 1.0" W (3RU) (17 cm x 13.3 cm x 2.5 cm)
Weight	1.0 lbs (0.45 kg)
Environmental	
Operating temperature range	-20° to +65°C (-4° to 149°F)
Storage temperature range	-40° to +85°C (-40° to 185°F)
Humidity	5% to 95% non-condensing
General	
Optical connector	SC/APC
Number of switches per module and switch configuration	Two 2x1 switches
Switch type	non-latching
Switching speed	< 5 ms typical, 10 ms max
Switching hysteresis	0.5 dB
Optical connector	SC/APC
	Hot plug-in/out
Optical	
Wavelength	Dual wavelength windows: 1263.5-1357.5 nm and 1423.5-1617.5 nm NOTE: The switch will pass <i>all</i> wavelengths within the two optical passbands of 1263.5-1357.5 nm and 1423.5-1617.5 nm in both directions. However, the unit's sensor and switching function will only respond to wavelengths inside this range: 1530.209 nm (ITU Ch 59)-1547.042 nm (ITU Ch 38). This minimizes the level of reflected Forward path DWDM wavelengths on ITU Ch 20 to Ch 39 but allows the loss of the Return path DWDM wavelengths on ITU Ch 40 to Ch 59 to be properly detected in the case of fiber cut when switching thresholds are set appropriately.
Input power	25 dBm max
Insertion loss	1.0 dB typical, 1.5 dB max
Isolation	55 dB min
Return loss	55 dB min
Polarization dependent loss	< 0.05 dB typical, 0.1 dB max
Power Requirements	
Input voltage	12 V _{DC}
Power consumption	1.6 W max
Local Controls and Monitoring	
Switching threshold (user-settable, independent for each input)	Range: -22 to +22 dBm (in 1 dB steps, accuracy ± 0.75 dB)
Operating mode	<ul style="list-style-type: none"> Auto: switch operates based on threshold setting Force to Ax (or Bx): switch permanently stays in position Ax (or Bx)
Wavelength	Select 1310 nm or 1550 nm region
Locally monitored parameters	chassis slot number, powering voltage, internal temperature, input optical power, switch position (“A” or “B”), operating mode (Auto or Forced-to-A or -B), wavelength
Front Panel Indicators	
Module status LEDs	<ul style="list-style-type: none"> Red “Alarm”: both inputs below threshold settings Blue “Access”: illuminated during communication access
Switch status LEDs	Green “A → OUT (switch in A position, or blinking if Forced to A) Yellow “B → OUT (switch in B position, or blinking if Forced to B)
Alarms	
	Service-affecting (DC failure, switch output below threshold, switch forced to A or B position) and non-service-affecting (high internal temperature, A or B input power below threshold)

ORDERING INFORMATION

Model Name	Description
OS32M2B-00-AS	Dual 2x1 Optical Switches

NOTE: All switches are configured with SC/APC connectors.

RELATED PRODUCTS

CH3000 Chassis	DR3450N Digital Return Receivers
Optical Transmitters	Optical Passives
Optical Patch Cords	Installation Services

Customer Care

Contact Customer Care for product information and sales:

- United States: 866-36-ARRIS
- International: +1-678-473-5656

Note: Specifications are subject to change without notice.

Copyright Statement: © 2019 CommScope, Inc. All rights reserved. ARRIS and the ARRIS logo are trademarks of CommScope, Inc. and/or its affiliates. All other trademarks are the property of their respective owners. No part of this content may be reproduced in any form or by any means or used to make any derivative work (such as translation, transformation, or adaptation) without written permission from CommScope, Inc and/or its affiliates ("CommScope"). CommScope reserves the right to revise or change this content from time to time without obligation on the part of CommScope to provide notification of such revision or change.

1513521_RevD_OS32M2B_Dual-Switch

10/2019 EA-30712

Ask us about the complete Access Technologies Solutions portfolio:

Headend Optics-CH3